

## [MS-VUVP-Diff]:

### VT-UTF8 and VT100+ Protocols

---

#### Intellectual Property Rights Notice for Open Specifications Documentation

- **Technical Documentation.** Microsoft publishes Open Specifications documentation (“this documentation”) for protocols, file formats, data portability, computer languages, and standards as well as overviews of the interaction among each of these technologies support. Additionally, overview documents cover inter-protocol relationships and interactions.
- **Copyrights.** This documentation is covered by Microsoft copyrights. Regardless of any other terms that are contained in the terms of use for the Microsoft website that hosts this documentation, you maycan make copies of it in order to develop implementations of the technologies that are described in the Open Specifications- this documentation and maycan distribute portions of it in your implementations using that use these technologies or in your documentation as necessary to properly document the implementation. You maycan also distribute in your implementation, with or without modification, any schema, IDL's schemas, IDLs, or code samples that are included in the documentation. This permission also applies to any documents that are referenced in the Open Specifications- documentation.
- **No Trade Secrets.** Microsoft does not claim any trade secret rights in this documentation.
- **Patents.** Microsoft has patents that maymight cover your implementations of the technologies described in the Open Specifications- documentation. Neither this notice nor Microsoft's delivery of the this documentation grants any licenses under those patents or any other Microsoft patents. However, a given Open Specification may Specifications document might be covered by the Microsoft Open Specifications Promise or the Microsoft Community Promise. If you would prefer a written license, or if the technologies described in the Open Specifications this documentation are not covered by the Open Specifications Promise or Community Promise, as applicable, patent licenses are available by contacting [iplg@microsoft.com](mailto:iplg@microsoft.com).
- **Trademarks.** The names of companies and products contained in this documentation maymight be covered by trademarks or similar intellectual property rights. This notice does not grant any licenses under those rights. For a list of Microsoft trademarks, visit [www.microsoft.com/trademarks](http://www.microsoft.com/trademarks).
- **Fictitious Names.** The example companies, organizations, products, domain names, e-mail email addresses, logos, people, places, and events that are depicted in this documentation are fictitious. No association with any real company, organization, product, domain name, email address, logo, person, place, or event is intended or should be inferred.

**Reservation of Rights.** All other rights are reserved, and this notice does not grant any rights other than as specifically described above, whether by implication, estoppel, or otherwise.

**Tools.** The Open Specifications documentation does not require the use of Microsoft programming tools or programming environments in order for you to develop an implementation. If you have access to Microsoft programming tools and environments, you are free to take advantage of them. Certain Open Specifications documents are intended for use in conjunction with publicly available standard standards specifications and network programming art, and assumes, as such, assume that the reader either is familiar with the aforementioned material or has immediate access to it.

## Revision Summary

Date	Revision History	Revision Class	Comments
5/11/2007	0.1	<u>New</u>	Version 0.1 release
8/10/2007	0.1.1	Editorial	Changed language and formatting in the technical content.
9/28/2007	0.1.2	Editorial	Changed language and formatting in the technical content.
10/23/2007	0.1.3	Editorial	Changed language and formatting in the technical content.
11/30/2007	0.1.4	Editorial	Changed language and formatting in the technical content.
1/25/2008	1.0	Editorial	Changed language and formatting in the technical content.
3/14/2008	2.0	Major	Updated and revised the technical content.
5/16/2008	2.0.1	Editorial	Changed language and formatting in the technical content.
6/20/2008	2.0.2	Editorial	Changed language and formatting in the technical content.
7/25/2008	2.0.3	Editorial	Changed language and formatting in the technical content.
8/29/2008	2.0.4	Editorial	Changed language and formatting in the technical content.
10/24/2008	2.0.5	Editorial	Changed language and formatting in the technical content.
12/5/2008	3.0	Major	Updated and revised the technical content.
1/16/2009	3.0.1	Editorial	Changed language and formatting in the technical content.
2/27/2009	3.0.2	Editorial	Changed language and formatting in the technical content.
4/10/2009	3.0.3	Editorial	Changed language and formatting in the technical content.
5/22/2009	4.0	Major	Updated and revised the technical content.
7/2/2009	4.0.1	Editorial	Changed language and formatting in the technical content.
8/14/2009	4.0.2	Editorial	Changed language and formatting in the technical content.
9/25/2009	4.1	Minor	Clarified the meaning of the technical content.
11/6/2009	4.1.1	Editorial	Changed language and formatting in the technical content.
12/18/2009	4.1.2	Editorial	Changed language and formatting in the technical content.
1/29/2010	4.1.3	Editorial	Changed language and formatting in the technical content.
3/12/2010	4.1.4	Editorial	Changed language and formatting in the technical content.
4/23/2010	4.1.5	Editorial	Changed language and formatting in the technical content.
6/4/2010	5.0	Major	Updated and revised the technical content.
7/16/2010	5.0	None	No changes to the meaning, language, or formatting of the technical content.
8/27/2010	5.0	None	No changes to the meaning, language, or formatting of the technical content.
10/8/2010	5.0	None	No changes to the meaning, language, or formatting of the

<b>Date</b>	<b>Revision History</b>	<b>Revision Class</b>	<b>Comments</b>
			technical content.
11/19/2010	5.0	None	No changes to the meaning, language, or formatting of the technical content.
1/7/2011	5.0	None	No changes to the meaning, language, or formatting of the technical content.
2/11/2011	5.0	None	No changes to the meaning, language, or formatting of the technical content.
3/25/2011	5.0	None	No changes to the meaning, language, or formatting of the technical content.
5/6/2011	5.0	None	No changes to the meaning, language, or formatting of the technical content.
6/17/2011	5.1	Minor	Clarified the meaning of the technical content.
9/23/2011	5.1	None	No changes to the meaning, language, or formatting of the technical content.
12/16/2011	6.0	Major	Updated and revised the technical content.
3/30/2012	6.0	None	No changes to the meaning, language, or formatting of the technical content.
7/12/2012	6.0	None	No changes to the meaning, language, or formatting of the technical content.
10/25/2012	6.0	None	No changes to the meaning, language, or formatting of the technical content.
1/31/2013	6.0	None	No changes to the meaning, language, or formatting of the technical content.
8/8/2013	7.0	Major	Updated and revised the technical content.
11/14/2013	7.0	None	No changes to the meaning, language, or formatting of the technical content.
2/13/2014	7.0	None	No changes to the meaning, language, or formatting of the technical content.
5/15/2014	7.0	None	No changes to the meaning, language, or formatting of the technical content.
6/30/2015	8.0	Major	Significantly changed the technical content.
10/16/2015	9.0	Major	Significantly changed the technical content.

# Table of Contents

<b>1</b>	<b>Introduction</b>	<b>6</b>
1.1	Glossary	6
1.2	References	7
1.2.1	Normative References	7
1.2.2	Informative References	7
1.3	Overview	7
1.3.1	VT-UTF8	8
1.3.2	VT100+	8
1.4	Relationship to Other Protocols	8
1.5	Prerequisites/Preconditions	8
1.6	Applicability Statement	8
1.7	Versioning and Capability Negotiation	8
1.8	Vendor-Extensible Fields	8
1.9	Standards Assignments	8
<b>2</b>	<b>Messages</b>	<b>9</b>
2.1	Transport	9
2.2	Message Syntax	9
2.2.1	VT-UTF8 and VT100+ for Serial/UPS	9
2.2.2	VT100+ Character Extensions for Serial/UPS	9
2.2.2.1	Client Display Terminal Color Extensions	10
2.2.2.1.1	Character Sequences	10
2.2.2.1.2	Color Values	10
2.2.2.2	Character and Key Extensions	11
2.2.3	VT100+ Character Extensions for Console Host	12
2.2.3.1	Client Display Terminal Color Extensions	12
2.2.3.1.1	Character Sequences	12
2.2.3.1.2	Color Values	13
2.2.3.2	Character and Key Extensions	14
<b>3</b>	<b>Protocol Details</b>	<b>15</b>
3.1	Server Details	15
3.1.1	Abstract Data Model	15
3.1.2	Timers	15
3.1.3	Initialization	15
3.1.4	Higher-Layer Triggered Events	16
3.1.5	Message Processing Events and Sequencing Rules	16
3.1.5.1	Sending VT-UTF8 and VT100+ Requests	16
3.1.5.2	Receiving VT-UTF8 and VT100+ Requests	16
3.1.5.3	Receiving Character and Key Extensions	16
3.1.6	Timer Events	17
3.1.7	Other Local Events	17
3.2	Client Details	17
3.2.1	Abstract Data Model	17
3.2.2	Timers	17
3.2.3	Initialization	17
3.2.4	Higher-Layer Triggered Events	17
3.2.5	Message Processing Events and Sequencing Rules	17
3.2.5.1	Sending VT-UTF8 and VT100+ Requests	17
3.2.5.2	Receiving VT-UTF8 and VT100+ Requests	18
3.2.5.3	Receiving Client Display Terminal Color Extensions	18
3.2.5.4	Receiving Character and Key Extensions	18
3.2.6	Timer Events	18
3.2.7	Other Local Events	18

<b>4</b>	<b>Protocol Examples</b> .....	<b>19</b>
4.1	VT-UTF8 Example for Serial/UPS .....	19
4.2	VT100+ Example for Serial/UPS .....	19
4.3	VT100+ Example for Console Host .....	19
<b>5</b>	<b>Security</b> .....	<b>21</b>
5.1	Security Considerations for Implementers .....	21
5.2	Index of Security Parameters .....	21
<b>6</b>	<b>Appendix A: Product Behavior</b> .....	<b>22</b>
<b>7</b>	<b>Change Tracking</b> .....	<b>24</b>
<b>8</b>	<b>Index</b> .....	<b>26</b>

# 1 Introduction

The VT-UTF8 and VT100+ Protocols are used for point-to-point serial communication for **terminal** control and headless server configuration.

Sections 1.5, 1.8, 1.9, 2, and 3 of this specification are normative ~~and can contain the terms MAY, SHOULD, MUST, MUST NOT, and SHOULD NOT as defined in [RFC2119]. Sections 1.5 and 1.9 are also normative but do not contain those terms.~~ All other sections and examples in this specification are informative.

## 1.1 Glossary

~~The~~This document uses the following terms ~~are specific to this document:~~

**American National Standards Institute (ANSI) character set:** A character set ~~(1)~~ defined by a code page approved by the American National Standards Institute (ANSI). The term "ANSI" as used to signify Windows code pages is a historical reference and a misnomer that persists in the Windows community. The source of this misnomer stems from the fact that the Windows code page 1252 was originally based on an ANSI draft, which became International Organization for Standardization (ISO) Standard 8859-1 [ISO/IEC-8859-1]. In Windows, the ANSI character set can be any of the following code pages: 1252, 1250, 1251, 1253, 1254, 1255, 1256, 1257, 1258, 874, 932, 936, 949, or 950. For example, "ANSI application" is usually a reference to a non-**Unicode** or code-page-based application. Therefore, "ANSI character set" is often misused to refer to one of the character sets defined by a Windows code page that can be used as an active system code page; for example, character sets defined by code page 1252 or character sets defined by code page 950. Windows is now based on **Unicode**, so the use of ANSI character sets is strongly discouraged unless they are used to interoperate with legacy applications or legacy data.

**ASCII:** The American Standard Code for Information Interchange (ASCII) is an 8-bit character-encoding scheme based on the English alphabet. ASCII codes represent text in computers, communications equipment, and other devices that work with text. ASCII refers to a single 8-bit ASCII character or an array of 8-bit ASCII characters with the high bit of each character set to zero.

**console host:** A server process that sends and receives data from a hosted text-based/character-mode application client.

**management console:** A remote computer that is used to interact with a local computer via a **terminal emulator**. A **management console** is often in a geographically different location than the local computer. A single **management console** ~~may~~can be used to interact with one or more local computers.

**terminal:** A text-based console. **Terminals** can be local or remote. A local **terminal** on a PC is typically an 80 × 25 text-format cell-based output that is displayed on a monitor.

**terminal emulator:** Software that runs a remote **terminal** on a **management console**. The **terminal emulator** uses a specified terminal type that must be agreed upon in advance via the local console and the remote **terminal**.

**Unicode:** A character encoding standard developed by the Unicode Consortium that represents almost all of the written languages of the world. The **Unicode** standard [UNICODE5.0.0/2007] provides three forms (UTF-8, UTF-16, and UTF-32) and seven schemes (UTF-8, UTF-16, UTF-16 BE, UTF-16 LE, UTF-32, UTF-32 LE, and UTF-32 BE).

**uninterruptible power supply (UPS):** A device that provides a backup short-term power source for occasions when utility power is lost. A **UPS** ~~may~~can be an intelligent device with which **management consoles** ~~can~~ interact.

**UTF-8:** A byte-oriented standard for encoding Unicode characters, defined in the Unicode standard. Unless specified otherwise, this term refers to the UTF-8 encoding form specified in [UNICODE5.0.0/2007] section 3.9.

**VT100:** A terminal type, as defined by [VT100]. [VT100] provides the definition for an English language, 80 × 25 text console.

**MAY, SHOULD, MUST, SHOULD NOT, MUST NOT:** These terms (in all caps) are used as defined in [RFC2119]. All statements of optional behavior use either MAY, SHOULD, or SHOULD NOT.

## 1.2 References

Links to a document in the Microsoft Open Specifications library point to the correct section in the most recently published version of the referenced document. However, because individual documents in the library are not updated at the same time, the section numbers in the documents may not match. You can confirm the correct section numbering by checking the Errata.

### 1.2.1 Normative References

We conduct frequent surveys of the normative references to assure their continued availability. If you have any issue with finding a normative reference, please contact dochelp@microsoft.com. We will assist you in finding the relevant information.

[RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", BCP 14, RFC 2119, March 1997, <http://www.rfc-editor.org/rfc/rfc2119.txt>

[VT100] Digital Equipment Corporation, "VT100 Series Technical Manual", September 1980, <http://vt100.net/docs/vt100-tm/ek-vt100-tm-002.pdf>

### 1.2.2 Informative References

[ACPI] Hewlett-Packard Corporation, Intel Corporation, Microsoft Corporation, Phoenix Technologies Ltd., Toshiba Corporation, "Advanced Configuration and Power Interface Specification", October 2006, <http://acpi.info/DOWNLOADS/ACPIspec30b.pdf>

[MSDN-ANSI] Microsoft Corporation, "Unicode and Character Sets", <http://msdn.microsoft.com/en-us/library/dd374083.aspx>

[MSDN-ConsoleRef] Microsoft Corporation, "Console Reference", [https://msdn.microsoft.com/en-us/library/windows/desktop/ms682087\(v=vs.85\).aspx](https://msdn.microsoft.com/en-us/library/windows/desktop/ms682087(v=vs.85).aspx)

[XTermControl] Moy, E., Gildea S., and Dickey T., "XTerm Control Sequences", <http://invisible-island.net/xterm/ctlseqs/ctlseqs.html>

## 1.3 Overview

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

The VT-UTF8 and VT100+ protocols are used for point-to-point serial client/server communication.

Typically, the client is a **terminal emulator** and acts as a **management console**; the server is a platform component that can be a basic input/output (BIOS), **uninterruptible power supply (UPS)** processor, service processor, or software driver. For example, the protocols allow server power management to be invoked from a serial console.

Alternatively, the server is a terminal emulator and acts as a **console host** for an application client. The application can be running locally on the same machine as the emulator or remotely over any form of network connection. The client application emits a sequence of characters that are transported to the terminal emulator server and presented to the user on the screen. The VT100+ protocol allows graphical signaling information to be interleaved with character data within the sequence of characters as it travels between the client and server.

### **1.3.1 VT-UTF8**

The VT-UTF8 protocol uses **UTF-8** encoding to allow **Unicode** characters to be used without conflicting with the original **VT100** protocol commands. Using Unicode characters, for example, allows non-English output on a client display.

### **1.3.2 VT100+**

The VT100+ protocol extends the original VT100 terminal specification ([VT100]) to support the use of color in a client display terminal, to define character sequences for function keys on the U.S. standard keyboard (101 keys), and to make provisions for additional graphic characters.

## **1.4 Relationship to Other Protocols**

This protocol extends the VT100 protocol, as specified in [VT100].

## **1.5 Prerequisites/Preconditions**

None.

## **1.6 Applicability Statement**

The VT-UTF8 and VT100+ protocols can apply to text-mode serial connections to physical hardware devices in emergency scenarios such as power outages.

A text-mode serial connection can alternatively be the connection between a client application and a console host window process. In this case, "serial" refers to the practice of signaling messages on a single stream.

## **1.7 Versioning and Capability Negotiation**

None.

## **1.8 Vendor-Extensible Fields**

None.

## **1.9 Standards Assignments**

None.



## 2 Messages

The following sections specify how the VT-UTF8 and VT100+ protocols are transported and message syntax.

### 2.1 Transport

The VT-UTF8 and VT100+ protocols are transmitted over a serial port (COM port) connection.

### 2.2 Message Syntax

#### 2.2.1 VT-UTF8 and VT100+ for Serial/UPS

The VT-UTF8 and VT100+ client console command request or server response consists of a single field that contains the "<ESC>" character followed by one or more characters. The entire sequence MUST be sent within 2 seconds of the initial <ESC>, as specified in sections 3.2.2 and 3.2.6.

**Command\_Sequence:** The character sequence containing the entire client request.

Character sequence	Description
<ESC>R<ESC>r<ESC>R	Reset. If the server is a BIOS with control of the serial port and reset is supported, the system MUST be reset within 5 seconds. If the server is a UPS, an application-specific integrated circuit (ASIC), a service processor, or a software driver, and has control of the serial port, the server MUST be reset within 1 second.
<ESC>(	Invoke the server ASIC or service processor. After detecting this command sequence, the server ASIC or service processor MUST take control of the server serial port for console input/output (I/O). The server ASIC or service processor MUST return an Acknowledge Sequence within 1 second.
<ESC>)	Invoke the UPS processor. After detecting this command sequence, the server UPS processor MUST take control of the server serial port for console I/O. The server UPS processor MUST return an Acknowledge Sequence within 1 second.
<ESC>*	Acknowledge sequence. This response MUST be returned by the server UPS, ASIC, or service processor before any other server response, and within 1 second after it is invoked.
<ESC>Q	Exit without displaying the user interface. The server UPS, ASIC, or service processor MUST immediately release control of the server serial port, without interaction with the client.
<ESC>^	Wake up. This requests that the server ASIC or service processor turn on the server within 1 second or wake the server from sleep state S1-S4 (for more information on sleep states, see [ACPI]). If the server is already turned on, server operation MUST NOT be disturbed. The server ASIC or service processor MUST return an Acknowledge Sequence within 1 second.

#### 2.2.2 VT100+ Character Extensions for Serial/UPS

The VT100+ character extensions conform to ANSI conventions for setting client display foreground and background colors. The VT100 standard, approved by the American National Standards Institute, defines meanings to coded sequences of characters passed from computer to terminal, as specified in [VT100]. The VT100+ extensions use the same general format of coded sequences of characters, but assign additional meanings for sequences that were not defined in the VT100 standard. The VT100+

character and key extensions also support selected keyboard keys and graphics characters that are not part of the original VT100 terminal specification. Function keys on a U.S. standard keyboard (101 keys) are not equivalent to similarly named keys on a VT100 terminal keyboard.

### 2.2.2.1 Client Display Terminal Color Extensions

The following sections list the character sequences and color values for the VT100+ extensions.

#### 2.2.2.1.1 Character Sequences

The following table lists the character sequences for the VT100+ extensions for uninterruptible power supply (UPS).

Character sequence	Description
<ESC>[%1m	Sets video mode and color, where %1 is the color value.
<ESC>[%1;%2;%3m	Sets multiple color values, where %1, %2, and %3 are the color values. Color values MUST NOT overlap.

#### 2.2.2.1.2 Color Values

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

The following table lists the color values for the VT100+ extensions.

Color value	Description
1	Video bold mode
5	Video blinking mode
30	Foreground black
31	Foreground red
32	Foreground green
33	Foreground yellow
34	Foreground blue
35	Foreground magenta
36	Foreground cyan
37	Foreground white
40	Background black
41	Background red
42	Background green
43	Background yellow

Color value	Description
44	Background blue
45	Background magenta
46	Background cyan
47	Background white

### 2.2.2.2 Character and Key Extensions

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

The following table lists the character sequences that correspond to the VT100+ character and key extensions for uninterruptible power supply (UPS).

**Note** If a modifier sequence (SHIFT modifier, ALT modifier, or CONTROL modifier) is not followed by a character sequence within 2 seconds, the modifier sequence is disregarded.

Character or key	Character sequence
HOME key	<ESC>h
END key	<ESC>k
INSERT key	<ESC>+
DELETE key	<ESC>-
PAGE UP key	<ESC>?
PAGE DOWN key	<ESC>/
F1 key	<ESC>1
F2 key	<ESC>2
F3 key	<ESC>3
F4 key	<ESC>4
F5 key	<ESC>5
F6 key	<ESC>6
F7 key	<ESC>7
F8 key	<ESC>8
F9 key	<ESC>9
F10 key	<ESC>0
F11 key	<ESC>!
F12 key	<ESC>@

Character or key	Character sequence
SHIFT modifier	<ESC><Ctrl>s
ALT modifier	<ESC><Ctrl>a
CONTROL modifier	<ESC><Ctrl>c
Reserved	<ESC>#
Reserved	<ESC>A
Reserved	<ESC>B
Reserved	<ESC>C
Reserved	<ESC>D
Reserved	<ESC>&
Reserved	<ESC>*
Reserved	<ESC>.
Reserved	<ESC>R
Reserved	<ESC>r

### 2.2.3 VT100+ Character Extensions for Console Host

~~Note: All of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it as an aid to the reader.~~

The VT100+ character extensions for console host conform to **ANSI** conventions for setting client display foreground and background colors. The extensions use the same general format of coded sequences of characters, but assign additional meanings to align with Xterm control sequences, as described in [XTermControl]. This provides interoperability with terminal emulators on Linux and Mac OS computers.<1>

#### 2.2.3.1 Client Display Terminal Color Extensions

The following sections list the character sequences and color values for the VT100+ extensions.

##### 2.2.3.1.1 Character Sequences

~~Note: All of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it as an aid to the reader.~~

The following table lists the character sequences for the VT100+ extensions for console host.

Character sequence	Description
<ESC>[m	Sets default video mode and color. Equivalent to <ESC>[0m.

Character sequence	Description
<ESC>[%1m	Sets video mode and color, where %1 is the color value.
<ESC>[%1;%2;...;%16m	Sets multiple color values, where %1, %2, and %16 are the color values. Up to 16 values <del>may can</del> be used separated by semicolons. Additional values beyond 16 are discarded.

### 2.2.3.1.2 Color Values

~~Note: All of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it as an aid to the reader.~~

The following table lists the color values for the VT100+ extensions for console host.

Color value	Description
0	Video default mode—clears flags and restores colors to default (when the session began)
1	Video bold/intense mode—implementation-specific color/font differentiation
4	Video underline mode
7	Video reverse mode—swaps foreground and background colors
24	Unset video underline mode
27	Unset video reverse mode
30	Foreground black
31	Foreground red
32	Foreground green
33	Foreground yellow
34	Foreground blue
35	Foreground magenta
36	Foreground cyan
37	Foreground white
39	Foreground default
40	Background black
41	Background red
42	Background green
43	Background yellow
44	Background blue
45	Background magenta

Color value	Description
46	Background cyan
47	Background white
49	Background default
90	Foreground black bold/intense
91	Foreground red bold/intense
92	Foreground green bold/intense
93	Foreground yellow bold/intense
94	Foreground blue bold/intense
95	Foreground magenta bold/intense
96	Foreground cyan bold/intense
97	Foreground white bold/intense
100	Background black bold/intense
101	Background red bold/intense
102	Background green bold/intense
103	Background yellow bold/intense
104	Background blue bold/intense
105	Background magenta bold/intense
106	Background cyan bold/intense
107	Background white bold/intense

### 2.2.3.2 Character and Key Extensions

~~Note: All of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it as an aid to the reader.~~

The following table lists the character sequences that correspond to the VT100+ character and key extensions for console host.

Character or key	Character sequence
Show Cursor	<ESC>[?h
Hide Cursor	<ESC>[?l (lowercase L)

## 3 Protocol Details

### 3.1 Server Details

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

This section applies to both the console host server and uninterruptible power supply (UPS) server implementations. <2>

#### 3.1.1 Abstract Data Model

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

When the uninterruptible power supply (UPS) server receives an escape character, it MUST enter an escape state for 2 seconds as it waits for additional characters.

When the console host server receives an escape character, it MUST wait indefinitely for additional characters.

For more information, see section 3.1.2.

#### 3.1.2 Timers

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

When an escape sequence is signaled to an uninterruptible power supply (UPS) server, the server MUST receive the escaped characters within 2 seconds. For example, the sequence "<ESC>(" invokes the service processor. The "(" character MUST be received by the server within 2 seconds of when "<ESC>" is received.

When an escape sequence is signaled to a console host server, the server MUST wait indefinitely for the next character before invoking the service processor.

#### 3.1.3 Initialization

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

The uninterruptible power supply (UPS) server requires no initialization.

The console host server requires initialization by the client application or by the user. Client applications can initialize the server through the SetConsoleMode function (see [MSDN-ConsoleRef]). Users or system administrators can set initialization to occur by default by setting the registry key at HKCU\VirtualTerminalLevel for each user account to a nonzero value.

### 3.1.4 Higher-Layer Triggered Events

The server has no higher-layer triggered events.

### 3.1.5 Message Processing Events and Sequencing Rules

The following sections specify the behavior of this protocol when receiving correct requests. Incorrect requests MUST be ignored.

#### 3.1.5.1 Sending VT-UTF8 and VT100+ Requests

The original VT100 protocol, as specified in [VT100], uses the **ASCII** character set. The UTF-8 algorithm MUST map a Unicode character into a string of 8-bit bytes. The number of 8-bit bytes depends on the bit width of the Unicode character, as shown in the following table.

Bit width	UTF8 encoding
0 - 7	0xxxxxxx
8 - 11	110xxxxx 10xxxxxx
12 - 16	1110xxxx 10xxxxxx 10xxxxxx

#### 3.1.5.2 Receiving VT-UTF8 and VT100+ Requests

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it in the Product Behavior appendix.~~

When a series of bytes is received by the server, it MUST be decoded into the appropriate 16-bit Unicode character. The leading byte MAY be 0x00000000.<3>

The decoded 16-bit Unicode character is then presented in the server representation, as specified in [VT100] table A-11.

If an escape sequence is received, the server processes all the characters in the escape sequence as a single action that is described by the escape sequence, instead of processing each literal character in the sequence.

#### 3.1.5.3 Receiving Character and Key Extensions

When a series of bytes is received by the server, it MUST be decoded into the appropriate 16-bit Unicode character. The leading byte MAY be 0x00000000.

The decoded 16-bit Unicode character is then presented in the server representation according to the tables in [VT100] table A-11.

If an escape sequence is received, the server processes all the characters in the escape sequence as a single action that is described by the escape sequence, instead of processing each literal character in the sequence.



### 3.1.6 Timer Events

If the server does not receive the escaped characters within 2 seconds of sequence initiation, the entire sequence is discarded.

### 3.1.7 Other Local Events

None.

## 3.2 Client Details

### 3.2.1 Abstract Data Model

When the client receives an escape character, it MUST enter an escape state for 2 seconds as it waits for additional characters. For more information, see section 3.2.2.

### 3.2.2 Timers

When an escape sequence is signaled, the client MUST receive the escaped characters within 2 seconds.

For example, the sequence "<ESC>(" invokes the service processor. The "(" character MUST be received by the server within 2 seconds of when "<ESC>" is received.

### 3.2.3 Initialization

The client requires no initialization.

### 3.2.4 Higher-Layer Triggered Events

The client has no higher-layer triggered events.

### 3.2.5 Message Processing Events and Sequencing Rules

The following sections specify this protocol's behavior when receiving correct requests. Incorrect requests MUST be ignored.

#### 3.2.5.1 Sending VT-UTF8 and VT100+ Requests

The original VT100 protocol, as specified in [VT100], uses the ASCII character set. The UTF-8 algorithm MUST map a Unicode character into a string of 8-bit bytes. The number of 8-bit bytes depends on the bit width of the Unicode character, as shown in the following table.

Bit width	UTF-8 encoding
0-7	0xxxxxxx
8-11	110xxxxx 10xxxxxx
12-16	1110xxxx 10xxxxxx 10xxxxxx

### **3.2.5.2 Receiving VT-UTF8 and VT100+ Requests**

When a series of bytes is received by the client, it MUST be decoded into the appropriate 16-bit Unicode character. The leading byte MAY be 0x00000000.

The decoded 16-bit Unicode character is then presented in the client representation according to the tables as specified in [VT100] table A-11.

If an escape sequence is received, the client processes all the characters in the escape sequence as a single action that is described by the escape sequence, instead of processing each literal character in the sequence.

### **3.2.5.3 Receiving Client Display Terminal Color Extensions**

When a series of bytes is received by the client, it MUST be decoded into the appropriate 16-bit Unicode character.

The leading byte MAY be 0x00000000. The decoded 16-bit Unicode character is then presented in the client representation according to the tables as specified in [VT100] table A-11.

If an escape sequence is received, the client processes all the characters in the escape sequence as a single action that is described by the escape sequence, instead of processing each literal character in the sequence.

### **3.2.5.4 Receiving Character and Key Extensions**

When a series of bytes is received by the client, it MUST be decoded into the appropriate 16-bit Unicode character.

The leading byte MAY be 0x00000000. The decoded 16-bit Unicode character is then presented in the client representation according to the tables as specified in [VT100] table A-11.

If an escape sequence is received, the client processes all the characters in the escape sequence as a single action that is described by the escape sequence, instead of processing each literal character in the sequence.

### **3.2.6 Timer Events**

If the client does not receive the escaped characters within 2 seconds of sequence initiation, the entire sequence is discarded.

### **3.2.7 Other Local Events**

None.

## 4 Protocol Examples

### 4.1 VT-UTF8 Example for Serial/UPS

A server wants to transmit the Unicode character stream that is represented by the following code point sequence.

```
<004D, 0430, 4E8C>
```

The VT-UTF8 encoding of the Unicode character stream would be

```
<4D D0 B0 E4 BA 8C>
```

where

- <4D> corresponds to 0x004D
- <D0 B0> corresponds to 0x0430
- <E4 BA 8C> corresponds to 0x4E8C

This stream maycan be transmitted to the client and then decoded by reconstructing the same Unicode character stream.

### 4.2 VT100+ Example for Serial/UPS

A user wishes to set the video mode to bold, the text foreground to black, and the background to green. The user sends the sequence

```
<ESC>[1,30,42m
```

as specified in section 2.2.2.1.1.

### 4.3 VT100+ Example for Console Host

The following sequence patterns can be found in section 2.2.3.1.1.

A user wishes to reset all color/font information in an area of text back to what it originally was when the session started. The user sends the sequence:

```
<ESC>[m
```

A user wishes to set a bright/bold green foreground color with a dark blue background color. The user has two options and sends either of the following sequences:

```
<ESC>[32;1;44m  
-OR-  
<ESC>[92;44m
```

Each item of the sequence will be applied in the order it is received. 32 will set the dark green foreground, 1 will turn it into a bright/bold foreground color, then 44 will set the dark blue background. Or 92 will set a bright green foreground in one step.

| A user MAY can specify multiple overlapping colors and they will be applied from beginning to end in the order received. The final applicable color in the sequence will be the resulting video mode. In the following example, a user sets blue foreground then magenta foreground:

```
<ESC>32;35m
```

The final result will be a magenta foreground mode.

## **5 Security**

### **5.1 Security Considerations for Implementers**

None.

### **5.2 Index of Security Parameters**

None.

## 6 Appendix A: Product Behavior

The information in this specification is applicable to the following Microsoft products or supplemental software. References to product versions include released service packs.

~~Note: Some of the information in this section is subject to change because it applies to a preliminary product version, and thus may differ from the final version of the software when released. All behavior notes that pertain to the preliminary product version contain specific references to it as an aid to the reader.~~

- Windows NT operating system
- Windows 2000 operating system
- Windows XP operating system
- Windows Server 2003 operating system
- Windows Vista operating system
- Windows Server 2008 operating system
- Windows 7 operating system
- Windows Server 2008 R2 operating system
- Windows Server 2012 operating system
- Windows Server 2012 R2 operating system
- Windows 10 operating system
- Windows Server 2016 ~~Technical Preview~~ operating system

Exceptions, if any, are noted below. If a service pack or Quick Fix Engineering (QFE) number appears with the product version, behavior changed in that service pack or QFE. The new behavior also applies to subsequent service packs of the product unless otherwise specified. If a product edition appears with the product version, behavior is different in that product edition.

Unless otherwise specified, any statement of optional behavior in this specification that is prescribed using the terms SHOULD or SHOULD NOT implies product behavior in accordance with the SHOULD or SHOULD NOT prescription. Unless otherwise specified, the term MAY implies that the product does not follow the prescription.

<1> Section 2.2.3: The console host terminal emulator sequences listed in this section are not supported on the following versions of Windows:

- Windows 2000
- Windows XP
- Windows Server 2003
- Windows Vista
- Windows Server 2008
- Windows 7
- Windows Server 2008 R2

- Windows Server 2012
- Windows Server 2012 R2
- [Windows 10](#)
- [Windows Server 2016](#)

<2> Section 3.1: The console host implementation applies only to Windows 10 and Windows Server 2016 ~~Technical Preview~~.

<3> Section 3.1.5.2: In the console host implementation, this service is provided by MultiByteToWideChar (see [MSDN-ANSI]) in respect to the current code page. The code page is loaded from the system on console host startup. It can be modified by the running application through GetConsoleOutputCP and SetConsoleOutputCP (see [MSDN-ConsoleRef]).

## 7 Change Tracking

This section identifies changes that were made to this document since the last release. Changes are classified as New, Major, Minor, Editorial, or No change.

The revision class **New** means that a new document is being released.

The revision class **Major** means that the technical content in the document was significantly revised. Major changes affect protocol interoperability or implementation. Examples of major changes are:

- A document revision that incorporates changes to interoperability requirements or functionality.
- The removal of a document from the documentation set.

The revision class **Minor** means that the meaning of the technical content was clarified. Minor changes do not affect protocol interoperability or implementation. Examples of minor changes are updates to clarify ambiguity at the sentence, paragraph, or table level.

The revision class **Editorial** means that the formatting in the technical content was changed. Editorial changes apply to grammatical, formatting, and style issues.

The revision class **No change** means that no new technical changes were introduced. Minor editorial and formatting changes may have been made, but the technical content of the document is identical to the last released version.

Major and minor changes can be described further using the following change types:

- New content added.
- Content updated.
- Content removed.
- New product behavior note added.
- Product behavior note updated.
- Product behavior note removed.
- New protocol syntax added.
- Protocol syntax updated.
- Protocol syntax removed.
- New content added due to protocol revision.
- Content updated due to protocol revision.
- Content removed due to protocol revision.
- New protocol syntax added due to protocol revision.
- Protocol syntax updated due to protocol revision.
- Protocol syntax removed due to protocol revision.
- Obsolete document removed.

Editorial changes are always classified with the change type **Editorially updated**.

Some important terms used in the change type descriptions are defined as follows:



- **Protocol syntax** refers to data elements (such as packets, structures, enumerations, and methods) as well as interfaces.
- **Protocol revision** refers to changes made to a protocol that affect the bits that are sent over the wire.

The changes made to this document are listed in the following table. For more information, please contact dochelp@microsoft.com.

Section	Tracking number (if applicable) and description	Major change (Y or N)	Change type
1.3 Overview	Updated content for Windows 10.	Y	Content update.
2.2.2.1.2 Color Values	Updated content for Windows 10.	Y	Content update.
2.2.2.2 Character and Key Extensions	Updated content for Windows 10.	Y	Content update.
2.2.3 VT100+ Character Extensions for Console Host	Added section with content for Windows 10.	Y	New content added.
2.2.3.1.1 Character Sequences	Added section with content for Windows 10.	Y	New content added.
2.2.3.1.2 Color Values	Added section with content for Windows 10.	Y	New content added.
2.2.3.2 Character and Key Extensions	Added section with content for Windows 10.	Y	New content added.
3.1 Server Details	Updated content for Windows 10.	Y	Content update.
3.1.1 Abstract Data Model	Updated content for Windows 10.	Y	Content update.
3.1.2 Timers	Updated content for Windows 10.	Y	Content update.
3.1.3 Initialization	Updated content for Windows 10.	Y	Content update.
3.1.5.2 Receiving VT-UTF8 and VT100+ Requests	Updated content for Windows 10.	Y	Content update.
6 Appendix A: Product Behavior	Updated product behavior notes for Windows 10.	Y	Product behavior note updated.

## 8 Index

### A

Abstract data model  
  client 17  
  server (section 3.1 15, section 3.1.1 15)  
Applicability 8

### C

Capability negotiation 8  
Change tracking 24  
Character extensions  
  receiving (section 3.1.5.3 16, section 3.2.5.4 18)  
  VT100+ (section 2.2.2 9, section 2.2.2.2 11, section 2.2.3.2 14)  
Character sequences - VT100+ extensions 10  
Client  
  abstract data model 17  
  display terminal color extensions (section 2.2.2.1 10, section 2.2.3.1 12)  
  higher-layer triggered events 17  
  initialization 17  
  local events 18  
  message processing 17  
  other local events 18  
  sequencing rules 17  
  timer events 18  
  timers 17  
Client Display Terminal Color extensions - receiving 18  
Color values - VT100+ extensions (section 2.2.2.1.2 10, section 2.2.3.1.2 13)

### D

Data model - abstract  
  client 17  
  server (section 3.1 15, section 3.1.1 15)  
Display terminal color extensions (section 2.2.2.1 10, section 2.2.3.1 12)

### E

Examples 19

### F

Fields - vendor-extensible 8

### G

Glossary 6

### H

Higher-layer triggered events  
  client 17  
  server 16

### I

Implementer - security considerations 21  
Implementers - security considerations 21  
Index of security parameters 21  
Informative references 7  
Initialization

- client 17
- server 15

Introduction 6

## **K**

Key extensions

- receiving (section 3.1.5.3 16, section 3.2.5.4 18)
- VT100+ (section 2.2.2.2 11, section 2.2.3.2 14)

## **L**

Local events

- client 18
- server 17

## **M**

Message processing

- client 17
- server 16

Messages

- overview 9
- syntax 9
- transport 9
- VT100+ Character Extensions for Console Host 12
- VT100+ Character Extensions for Serial/UPS 9
- VT-UTF8 and VT100+ for Serial/UPS 9

## **N**

Normative references 7

## **O**

Other local events

- client 18
- server 17

Overview 7

Overview (synopsis) 7

## **P**

Parameters - security 21

Parameters - security index 21

Preconditions 8

Prerequisites 8

Product behavior 22

## **R**

References 7

- informative 7
- normative 7

Relationship to other protocols 8

## **S**

Security 21

- implementer considerations 21
- parameter index 21

Sequencing rules

- client 17
- server 16

Server  
  abstract data model (section 3.1 15, section 3.1.1 15)  
  higher-layer triggered events 16  
  initialization 15  
  local events 17  
  message processing 16  
  other local events 17  
  overview 15  
  sequencing rules 16  
  timer events 17  
  timers 15  
Standards assignments 8  
Syntax - message 9

## T

Timer events  
  client 18  
  server 17  
Timers  
  client 17  
  server 15  
Tracking changes 24  
Transport 9  
Transport - message 9  
Triggered events - higher-layer  
  client 17  
  server 16

## U

UTF8  
  receiving requests 16  
  sending requests 16

## V

Vendor-extensible fields 8  
Versioning 8  
VT100+  
  character extensions (section 2.2.2 9, section 2.2.2.2 11, section 2.2.3.2 14)  
  key extensions (section 2.2.2.2 11, section 2.2.3.2 14)  
  message syntax 9  
  overview 8  
  receiving requests (section 3.1.5.2 16, section 3.2.5.2 18)  
  sending requests (section 3.1.5.1 16, section 3.2.5.1 17)  
VT100+ Character Extensions for Console Host message 12  
VT100+ Character Extensions for Serial/UPS message 9  
VT100+ extensions - color values (section 2.2.2.1.2 10, section 2.2.3.1.2 13)  
VT-UTF8  
  message syntax 9  
  overview 8  
  receiving requests 18  
  sending requests 17  
VT-UTF8 and VT100+ for Serial/UPS message 9